

## PULSEFLEX



**TAKE YOUR HIFI WITH YOU.** The PULSE FLEX is a game-changing 2-way speaker that delivers the best of both performance and portability. This ultra-compact wireless speaker will change the way you think about personal audio.

Mount a pair in the corners of a large room, hide one on a bookshelf, take one out to the patio table or throw one in your bag for a picnic – the PULSE FLEX allows you the true flexibility you've been waiting for in a multi-room streaming music system. And for the first time ever, Bluesound extends the concept of home HiFi beyond the home itself.

Like all PULSE all-in-one Players, when used in pairs, the PULSE FLEX is designed to create a large stereo sound field that will expand the way you think about portable speaker performance.

An optional battery pack delivers up to 8 hours of high-res streaming autonomy, and all Bluesound Players are enabled with Bluetooth aptX<sup>®</sup>. You can now enjoy HiFi performance virtually anywhere you want to go.

DIGITAL AMPLIFIER

WIFI + ETHERNET

aptX® BLUETOOTH WIRELESS BUILT-IN

FLEXIBLE IN/OUTDOOR PORTABILITY

1x 25mm (1") TWEETER DRIVER

1x 89mm (3.5") BASS DRIVER

USB TYPE-A INPUT

**OPTICAL & ANALOG INPUTS** 

**HEADPHONE OUTPUT** 

ASSIGNABLE PRESETS

RECHARGEABLE BATTERY (SOLD SEPARATELY)

**BLACK OR WHITE FINISH** 



## **PULSE FLEX Specifications**

**Supported Operated Systems:** Windows Vista, 7, 8, Apple Macintosh OS X 7-10

Supported File Formats: MP3, AAC, WMA, WMA-L, OGG, FLAC, ALAC, WAV, AIFF

Native Sampling Rates: 32 - 192kHz Bit Depths: 16 - 24

Features:

Play/Pause Button: Hard Button
Volume Control Buttons: Hard Button
Previous/Next Track Buttons: Hard Button
Preset Buttons: Hard Button

Processor: ARM® Cortex™ -A9, 1GHz

Distortion: THD+N, 0.030%

Amplification: Digital

Power Output: 20W x 2 Bi-Amplified

Speakers: 1x 89mm (3.5"), 1x 25mm (1")

Frequency Response: 45Hz - 20kHz

 ${\bf Connections:}$ 

Power: Universal bi-pin AC cord input (100 - 240AC)

Ethernet/LAN:Ethernet RJ45, 100BaseTWiFi Built In:802.11 b/g/n WiFiBluetooth Built In:Bluetooth 4.0 with aptXOptical/Analog Input:Combo - Toslink/3.5mm

USB IN: Type A (Fat32 or NTSF Formatted)
USB: Type B (mini) for product servicing

Headphone Output: 3.5mm Stereo


Power Consumption (Idle): 14W
Finish: Black/White

Dimensions (Unit):

 $\begin{array}{lll} (W \times H \times D) & 125 \times 183 \times 100 \text{mm} \\ (W \times H \times D) & 4.92 \times 7.2 \times 3.9 \text{ in} \\ \textbf{Weight:} & 1.23 \text{kg}/2.71 \text{lbs} \\ \end{array}$ 

## Included Accessories:

120V AC Power Cord or 230V AC Power Cord Toslink Optical to 3.5mm Mini Adaptor Safety/Warranty Guide Quick Setup Guide



4.92"-

